

CONTROL4 DRIVER V4

FOR MIRAGE MEDIA SERVER

COMPATIBLE WITH



Control4® OS 2.8+

MIRAGE

Overview

The Autonomic Control4® Version 4 driver suite allows for convenient programming of all models of the Mirage Media Server (MMS) in a Control4 environment. The driver suite is compatible with systems running at least Control4 OS 2.8+ or higher and MMS firmware 5.3 or higher.

Autonomic Mirage Media Servers offer up to six audio outputs (MMS-5A), each with full access to local and internet-based content such as Deezer, iHeartRadio, Murfie, Napster®, Pandora®, SiriusXM®, Slacker Radio®, Spotify, TIDAL, and Tuneln, bridging them together with revolutionary TuneBridge® functionality. Each output of the server is fully and discretely controllable.

This driver suite was developed and tested with Control4 2.8 running on an HC-800 and several control interfaces, including Control4's desktop application, iPad app, and portable touchpanels.

Features

Version 4 of the MMS driver suite integrates fully into the Control4 system. It offers individual drivers for each of the streaming services as well as a full browser for all content, local and streaming. Both the individual drivers and full browser provide access to the complete MMS feature set including TuneBridge, playlists, favorites, and queue management.

Each service driver will automatically select an output on the server for use. Additionally, there is a central driver called MCP and a driver for Instances.

How the Drivers Communicate

This suite of drivers works by truly connecting the basic data of the Control4 Rooms to the MMS.

While each service and Instance driver connects to the MMS for browsing and now playing control respectively, the MCP driver handles all major communication with the MMS. The service and Instance drivers communicate with each other through the MCP driver.

Getting Started

The Autonomic Control4 Version 4 driver suite for all models of the Mirage Media Server (MMS) is compatible with systems running at least Control4 OS 2.8 or higher and MMS firmware 5.3 or higher.

Please verify that you are running the latest version of Composer and the Mirage Media Server firmware is up to date before proceeding.

You can check and update your firmware version on the MMS by going to the **Firmware** tab on the server's web configuration (<http://server-ip/config/Software.aspx>) or from the Autonomic Dealer Zone company account associated with the MMS (<http://dealerzone.autonomic-controls.com>).

The latest Composer software is available from Control4's dealer site (<https://dealer.control4.com>).

Configuration

ADDING THE DRIVERS TO YOUR PROGRAM

1. In Composer, in the **System Design** section, select the **Search** tab on the far right. Next, search for **Autonomic** and/or **Mirage** in the search field. All of our drivers should appear in the results list.
2. Before adding other drivers, the central driver, called **MCP for Mirage Media Server**, needs to be added to the project. It is important to note that only one MCP driver is supported per project.
3. Add the Instance drivers, called Instance for **Mirage Media Server**. Add one copy of the Instance driver per Instance you'd like to include in your project. These drivers will automatically bind to the MCP driver as **RF_AUTONOMICNET_INSTANCE** bindings starting at the top of the output bindings. We recommend adding one Instance driver per output on your MMS and setting those you will not use to disabled. By default, the Instance drivers 'Properties' and 'MMS Instance' is set to Player_A, so make sure you set each Instance driver to the appropriate value. Ensure that the Instance drivers are bound to the same **RF_AUTONOMICNET_INSTANCE** position as what physically matches the server (Main = 1, Player_A = 2, etc.).
4. Add drivers for the streaming services for accounts that your client has. These drivers are called **[Service name] for Mirage Media Server** and they will automatically bind to the MCP driver starting at the top of the input bindings as **RF_AUTONOMICNET_SERVICE**.

BINDING THE DRIVERS TO THE REST OF THE SYSTEM

Each Instance driver has several output types, but only one should be bound. The choice of TOSLINK S/PDIF, coax S/PDIF, or an RCA pair allows the same driver to be used for all possible MMS output types. Bind the audio output type that matches the physical output on the MMS for the Instance the driver is controlling to the input on the switch that the MMS output is physically wired to. For example, if the driver is representing the **Main** output on an MMS-5A or MMS-2A, bind the coax S/PDIF output to the switch whereas if it's representing **Player_A** on any model MMS, bind the RCA pair. Previous generation MMS' should use the TOSLINK S/PDIF output for their **Main** outputs.

CONFIGURING THE DRIVERS

Only the MCP driver needs the IP of the MMS. This will auto populate if the MCP driver was added through SDDP discovery. If the driver was added manually or the IP did not auto populate, select the MCP driver under **System Design** and enter the IP of the MMS you'd like to control. MCP will communicate this information to the other drivers. Each Instance driver needs to know which Instance it represents. **It's very important to press the *Update Rooms* button after making any change to a Room.** Adding, removing, changing the name of, or changing the available devices in a Room without pressing **Update Rooms** will cause the MMS to get out of sync with the current settings.

CONFIGURING THE MMS

1. Once all drivers are in place and connections bound, select the MCP driver under **System Design**.
2. Select the **Actions** tab, then click **Configure MMS**. The driver will connect to the MMS and configure it to match your program.

HIDING DRIVERS

It is possible to hide the Instance drivers from the navigators. We only recommend hiding Instance drivers in navigators when all Instances are available in all rooms.

1. Select the room under **System Design**.
2. Select the **Navigator** tab.
3. Double-click on the **Listen** option under **Menu**.
4. Move drivers to the hidden side of the window that pops up. **We strongly recommend doing this with all of the Instance drivers under this condition.**

For advanced users: If an MMS output has a valid audio path to multiple rooms, but it is desired to play specifically in one room and none others, hiding this Instance driver in all rooms but the room where it will be available will accomplish this.

Properties

MCP

IP address - the address of the MMS being controlled. This auto populates when the driver is added through SDDP.

Status - the status of the IP connection to the server

Configuration Status - whether or not the driver has configured the server since the last Control4 program change involving these drivers

Coax Bit Rate Format - the bit depth and sample rate the MMS's digital output should use

Debug Mode - Turns Lua debugging on or off

INSTANCE

MMS Instance - Sets which output on the server the driver represents and controls

Enabled - Enables the Instance

Debug Mode - Turns Lua debugging on or off

SERVICE DRIVERS

Debug Mode - Turns Lua debugging on or off

Actions

CONFIGURE MMS

This action informs the MCP server of the available outputs based on the drivers present in the Control4 program.

REFRESH DRIVER STATE

The MCP server makes every effort to maintain up to date information on all of its bound Service drivers, but this can be forced using this action.

UPDATE ROOMS

The MCP driver requires a current list of Autonomic services for each room in the project. **It is important to press this button after adding or removing rooms and after completing initial setup.**

Limitations

Workflows that require a series of text input boxes are not supported due to the inability to asynchronously request a keyboard. Additionally, as message boxes are added or changed, drivers will have to be updated.

Troubleshooting

PLAYING CONTENT IS NOT HEARD IN ROOM

Check that each Instance driver has the correct MMS Instance selected. Incorrectly configuring the Instances can cause the wrong input on the audio switch to be selected. Also, confirm that the server is configured properly by clicking the **Configure MMS** action on the **Actions** tab for the MCP driver in **System Design**.

SERVICE DRIVERS CANNOT BROWSE

Ensure that MCP has the correct IP address. This value is communicated to all other drivers. If it is incorrect, those drivers will not be able to communicate with the MMS. If the issue persists, turn Lua logging on for the Service driver in question and try to browse. If the logs show a failure to communicate, there may have been a miscommunication between drivers. Re-enter the IP address into MCP to force the correct value.

Technical Support

If you require further assistance with configuring the Control4 Driver Suite Version 4 for the Mirage Media Server, please contact Autonomic Technical Support at +1 914-598-1647, option 2, or email support@autonomic-controls.com. You can also visit the Autonomic Knowledge base (<http://www.autonomic-controls.com/kb>) for troubleshooting information and access to submitting a support ticket.